

240718

	RA122	RA121	RD122	RD121	RD82	RE82	RE121
Channels	12	12	12	12	8	8	12
Watts/Channel	2400	1200	2400	1200	2400	2400	1200
Total Wattage	28800	14400	28800	14400	19200	19200	14400
Control Protocol	DMX512 / Remote Stations	DMX512 / Remote Stations	DMX512	DMX512	DMX512	DMX512	DXM512
Built-In Chaser	-	-	8 Chases	8 Chases	8 Chases	-	-
Dim/Non-Dim Control	Yes						
Soft Start	Yes						
Softpatch	Yes	Yes	Yes	Yes	Yes	-	-
Set Levels Locally	Yes	Yes	Yes	Yes	Yes	ON / OFF Only	ON / OFF Only
Local Scene	100 Scenes	100 Scenes	1	1	1	-	-
Power Input	120/208VAC Three Phase, 80A each Leg OR 120/240VAC Single Phase, 120A each Leg	120/208VAC Three Phase, 40A each Leg OR 120/240VAC Single Phase, 60A each Leg	120/240 VAC, 120A/Phase, 50/60 Hz Two Phase	120/240 VAC, 60A/Phase, 50/60 Hz Two Phase	120/240 VAC, 80A/Phase, 50/60 Hz Two Phase	120/240 VAC, 80A/Phase, 50/60 Hz Two Phase	120/240 VAC, 60A/Phase, 50/60 Hz Two Phase
Power Input Connections	Terminal Block						
Load Output Connections	Duplex or Terminal Strip Optional Patchbay or Socapex	Duplex or Terminal Strip Optional Patchbay or Socapex	Duplex or Terminal Strip Optional Socapex	Duplex or Terminal Strip Optional Stagepin, Patchbay or Socapex			
Overload Protection	20A Magnetic Circuit Breakers	10A Magnetic Circuit Breakers	20A Magnetic Circuit Breakers	10A Magnetic Circuit Breakers	20A Magnetic Circuit Breakers	20A Magnetic Circuit Breakers	10A Fuses
Filter Rise Time	450 uSec	350 uSec	350 uSec	350 uSec	350 uSec	350 uSec	350 uSec
UL-508 Compliant	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Weight (boxed)	50 pounds	29 pounds	50 pounds	31 pounds	32 pounds	32 pounds	29 pounds
OPTIONS							
CB	Circuit Breaker Option Available for RE121D						
230V	230 Volt Operation						
ST	Stagepin Outlet Panel *Non UL-508 Compliant						
SO	Socapex Outlet Panel *Non UL-508 Compliant						
PL	Powerlock Outlet Panel *Non UL-508 Compliant						
DP	Edison Duplex Outlet Panel						
XT	Terminal / Barrier Connector Strip with Knockout Cover						