

# Wireless DMX

- Free Standing Wireless Receiver Box
- W-DMX™ Dependability
- Control (1) Full Universe/512 DMX Channels
- Reliability of FHSS TDMA Communication
- 83 Channel Hopping 2.45GHz Band
- 1400 Feet Indoor Range
- 5 Pin DMX512 Output
- 12V DC Adapter (Included)

WSRFX  
Wireless DMX Receiver



The WSRFX is a compact RF receiver unit which can receive a DMX512 lighting control signal from a compatible wireless DMX transmitter or wireless equipped DMX lighting console. The received DMX signal is available on a standard DMX 5 pin Female XLR connector for a connection to a normal wired DMX system. The WSRFX is supplied with a UL listed external power supply and an antenna.

The WSRFX operates with a single specific compatible W-DMX™ transmitter or equipped console at a time. Connected receivers receive and relay the same information they would get using a cable connected to a DMX lighting console. Multiple WSRFX receivers, on the same universe, may be operated with a single transmitter or console.

The wireless system uses the 2.45 GHz band and operates at low power (< 100mW). The operating range is approximately 1400 ft. indoors and about 4000 ft. for outdoor operation. This range could vary significantly depending on the surrounding conditions. A link between one or more WSRFX receivers and one compatible transmitter unit is invoked to enable wireless operation. The linking operation is performed at the transmitter. Once linked, the receiving units can operate ONLY with the assigned transmitter. The link is retained even when the receiver and/or transmitter are powered off.

Receiver units may be released from the link either globally at the transmitter or locally at the receiver. If released globally, at the transmitter, then ALL linked receivers will be released simultaneously. If unlinked locally, at the receiver, then ONLY that receiver will be released.

## SPECIFICATIONS

Operating Frequency:	2.45 GHz band	Indicators:	DMX / Link Status
Range:	Indoor 1400 ft.	Power Supply:	External, 12VDC, 1 amp
RF Signal Type:	RF/FHSS & TDMA	DMX Connection:	5 Pin Female XLR
Antenna Connector:	SMA Type	Dimensions:	3.25" W x 2" H x 5" D
Controls:	Link / Release Link	Weight:	.5 Pounds